

# NYLA-3G/UHD/HDR STRAIGHT MOBILE PRODUCTION UNIT

#### **FEATURES & HIGHLIGHTS:**

Grass Valley K-Frame XP Compact Switcher; Studer Vista 5 M3; Grass Valley LDK 86N HD/UHD Cameras; 2 31" Sony BVM-HX3110 Monitors in Production Monitor Wall; 2 Sony BVM-HX3110 in Video; Multiviews in Production, Audio, Video, and Tape; EVS W/ 2 42" LCD Monitors.

#### **ENGINEERING:**

- Ross FR12 Router 160 in 160 out ,10 Frame Syncs Built In the Router, 15 For-A Up/Down/Cross/CC, Madi and Dante Directly To and From Router, 32 In 32 Out Fiber 1/0
- 6 External Multiviewers
- 1 Video Stage Box 16 Fiber to BNC and BNC to Fiber Converter
- Field Ferrofish A32pro Dante for Madi and Dante Needs
- 48 Port Managed Field Switch for All Network Needs

## VIDEO:

- 2 Sony 31" BVM-HX3110 Monitors
- 4 Leader 5300a Scopes
- Multiviewer for Camera Repeats
- Grass Valley LDK 86N HD/UHD Cameras (Wired for Up to 12)

# PRODUCTION:

- Grass Valley K-Frame XP Compact Switcher (UHD/3G/HD) 80 In 40 Out, 5 M/E 8 Keyers per M/E
- 2 Sony 31" BVM-HX3110 Monitors
- 2 55" and 2 49" Boland Monitors for Multiviewer Needs

# AUDIO:

- Studer Vista 5 M3 W/ Vistamix and 42 Faders on the Surface
- Studer Stage Box W/ SMPTE Fiber (Optional)

## **RECORD & PLAYBACK:**

- Up to 32 HD Record Channel Capability (8 Channel UHD)
- Wired for Two 8-channel DDRs
- 10G Managed Network for Quicker Media Transfers

#### COMMUNICATIONS:

- Riedel Artist 128 Matrix
- 2 Connect Trio Telephone Interfaces

#### **GRAPHICS:**

Wired for 1 CG Machine

## **FORMAT SUPPORT:**

- 720p 60Hz, 720p 59.94Hz, 720p 50Hz
- 1080i 30Hz, 1080i 29.97Hz, 1080i 25Hz,
- 1080p 30Hz, 1080p 29.97Hz, 1080p 25Hz, 1080p 24Hz, 1080p 23.98Hz
- 1080p-a 60Hz, 1080p-a 59.94Hz, 1080p-a 50Hz
- 3840x2160P 59.94Hz, 50Hz, 29.97Hz, 23.98 Hz

## **POWER REQUIREMENTS:**

A-Unit:

200 AMP, Single Phase, 208 Volt, 3 Wire

# **SPACE REQUIREMENTS:**

• A-Unit: (All Measurements Without Tractor)

51' Long x 13'6" High x 8'5" Wide–Closed (W/ the Longest Tractor Length is 72') 53' Long x 13'6" High x 12'6" Wide–W/ HVAC Flaps Open & Stairs/Platform